



Operation manual for MAV cards DIP switch

1-card 1-port cards (MINI-MANAGER SERIES 9x9,18x18,36x36)


1080P HDMI/MAV Input Cards

Picture	Features
	<ul style="list-style-type: none"> ➤ Seamless switch ➤ Universal inputs(DVI-I port) ➤ Support HDMI/VGA/CVB/YPBPR with different adapters ➤ 3.5mm audio embedded ➤ 8-pin DIP switch for scaling ➤ HDCP compliant

1080P MAV Input Card DIP Switch													
Customize Resolution				Input Source Select				Image or Audio Select			IR Function		
DIP 3	DIP 4	DIP 5	Description	DIP 7	DIP 1	DIP2	Description	DIP 6	Version	Description	DIP 8	Description	
0	0	0	1024*768	1	0	0	CVBS Input	1	Version 2	HDMI audio input	0	IR off	
0	0	1	1360*768	1	0	1	YPBPR input	0		3.5mm audio input	1	IR on	
0	1	0	1920*1200	1	1	0	VGA input						
0	1	1	720P/60	1	1	1	DVI input						
1	0	0	Null	0			Signal Auto detect						
1	0	1	Null										
1	1	0	1080P/50										
1	1	1	1080P/60										

* The maximum resolution of this card only can up to 1080P@60Hz
 *Can support 8-pin DIP switch, installer can manually set a fixed resolution, such as if needs a fixed 1920x1200 resolution, can set up the DIP switch DIP3, DIP4 and DIP5 to be "0,1,0".

1080P MAV Output Card

Picture	Features
	<ul style="list-style-type: none"> ➤ Seamless switch ➤ Universal output(DVI-I port) ➤ Support HDMI/VGA/CVB/YPBPR with different adapters ➤ 3.5mm audio de-embedded ➤ 8-pin DIP switch for scaling ➤ HDCP compliant

1080P (MAV, SDI)Output Card DIP Switch											
Resolution Set Up						Color Space		Image		IR	
D2	D3	D4	D5	D6	Description	D1	Description	D7	Description	D8	Description
0	0	0	0	0	1024*768@60	0	RGB	0	Image mirror	0	IR ON
0	0	0	0	1	800*600@60	1	YUV	1	Normal display	1	IR OFF
0	0	0	1	0	1280*800@60						
0	0	0	1	1	1280*1024@60						
0	0	1	0	0	1360*768@60						
0	0	1	0	1	1366*768@60						
0	0	1	1	0	1400*1050@60						
0	0	1	1	1	1440*900@60						
0	1	0	0	0	1680*1050@60						
0	1	0	0	1	1600*1200@60						
0	1	0	1	0	1920*1200@60						
0	1	0	1	1	1600*1200@60						
0	1	1	0	0	1680*1050@60						
0	1	1	0	1	1400*900@75						
0	1	1	1	0	640*480@75						
0	1	1	1	1	800*600@75						
1	0	0	0	0	480i@60						
1	0	0	0	1	576i@50						
1	0	0	1	0	480P@60						
1	0	0	1	1	576P@50						
1	0	1	0	0	1280*720@24						
1	0	1	0	1	1280*720@25						
1	0	1	1	0	1280*720@30						
1	0	1	1	1	1280*720@50						
1	1	0	0	0	1280*720@60						
1	1	0	0	1	1080i@50						
1	1	0	1	0	1080i@60						
1	1	0	1	1	1080P@24						
1	1	1	0	0	1080P@25						
1	1	1	0	1	1080P@30						
1	1	1	1	0	1080P@50						
1	1	1	1	1	1080P@60						



* The maximum resolution of this card only can up to 1080P@60Hz
 *Can support 8-pin DIP switch, installer can manually set a fixed resolution, such as if needs a fixed 1080i resolution, can set up the DIP switch DIP3, DIP4, DIP 5 and DIP6 to be "1,1,0,0,1".