



## How to customize Your Logo on matrix switcher

Step 1: Get the upgrade firmware ready

**Step 2:** In the firmware, will need to have 3 pictures **"banner" "logo"** and **"startup"** with the wanted contents/logo on, please make sure don't change the picture names, and the format is **.png**.

nx6-upgrade > rootfs > home > app > images > default ~									ひ ク 捜索"default"		
r r	8 1 2 3 3 3 a2a	a2a_	1 1 2 2 3 3 a2n	1 1 2 2 3 3 a2n_	banner	1 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2	8 1 2 2 3 2 3 btn_act_1	1 1 2 2 3 3 btn_act_2	1 1 2 2 3 3 btn_act_2_	1 1 2 2 3 3 3 btn_act_3	
٢	8 1 2 2 3 3 btn_act_3	1 1 2 2 3 3 btn_act_4	1 1 2 2 3 3 btn_act_4_	btn_act_5	btn_act_5_	btn_act_6	btn_act_6_	btn_in	btn_in_	swiтcн 🗭 btn_menu_1	
	SWITCH	SCENE DI	SCENE	SETUP 🗙	SETUP 🗙	VIEW	VIEW	02a	02a_	1 1 2 2 3 3 02n	
	1 1 2 2 3 3 o2n_	save	save_	script	script_	LOTY Iogo	A WolfFack Company startup_lcd	startup	]		

**Step 3:** Have this firmware compressed to the .zip file. Then the firmware is ready to go.



**Step 4:** Make sure the matrix switcher is connected with the control PC by LAN, and logo in with the browser.

Matrix		Manager	Switch	Scene	Caption	Setup	Login	More 🕶
	Please legin							
	username							
	password							
	Login							
© 2016 Company, Inc. V1.1.0							В	ack to top

**Step 5:** After login, go to the "More" interface and will see the "Upgrade" button

Step 6: Click the "upgrade" button, will show the window to upgrade

**Step 7:** After choosing the right firmware and click to upgrade, then matrix switch will reboot itself, just wait for 30 seconds, your customized logo/startup screen is all set.





Here's a Youtube demo video: <u>https://youtu.be/0WoiwdF3r11</u>