

## UDP commands control

**UDP broadcast**(for all devices are in the same LAN.)  
IP address 239.1.0.1, port number is 8804

**TCP/UDP unicast**(For devices are from different LAN)  
TCP port number is 6006, IP address will the device's IP  
UDP port number is 6004, IP address will the device's IP

### Scenes Save/Recall/Delete

**"wallid"**: for the video wall devices' ID

**"outdevlist"**: for the matrix devices' ID

**"name"**: for the scenes name(only for letter)

**"id"**: scene ID

**"Type"**: 0-for audio and video, 1- for video, 2-for audio

#### **Scene Save**

```
{"cmd":"savescene","wallid":1,"name":"scene-01", "id":0,"type":0}  
{"cmd":"savescene","outdevlist":1,"name":"scene-01",  
"id":0,"type":0}
```

#### **Scene Recall**

```
{"cmd":"callscene","wallid":1,"id":0,"type":0}  
{"cmd":"callscene","outdevlist":1,"id":0,"type":0}
```

#### **Scene Delete**

```
{"cmd":"deletescene","wallid":1,"id":0,"type":0}  
{"cmd":"deletescene","outdevlist":1,"id":0,"type":0}
```

### Matrix Swtching

**"wallid"**: for the video wall devices' ID

**"outdevlist"**: for the matrix devices' ID

```
{"cmd":"openwindow","wallid":[1,2,3.....],"id":0,"x":0,"y":0,"width":1920,"  
height":1080,"type":0,"protocol":0,"url":"192.168.1.71:9705/channel=0/st  
ream=0","suburl":"192.168.1.71:9705/channel=0/stream=1","stream":0 }  
{"cmd":"openwindow","outdevlist":[1,2,3.....],"id":0,"x":0,"y":0,"width":  
1920,"height":1080,"type":0,"protocol":0,"url":"192.168.1.71:9705/channe  
l=0/stream=0","suburl":"192.168.1.71:9705/channel=0/stream=1","strea  
m":0 }
```

### Video Wall or Matrix input clear

```
{"cmd":"clearsources","wallid":1}  
{"cmd":"clearsources","outdevlist":[54]}
```

### Adjust Window Size

```
{"cmd":"changewindow","wallid":1,"id":0,"x":200,"y":200,"width":960,"height":540}
```

```
{"cmd":"changewindow","outdevlist":[54],"id":0,"x":200,"y":200,"width":960,"height":540}
```