

IR REMOTE CONTROL GUIDE

Modular 8x8 Matrix Switcher



*Please NOTE: The EDID is not functional on this IR remote control for this 9x9 Modular Matrix Switcher as it couldn't support the EDID management.

Inputs Switch:

number(1~8) ---> SWITCH ----> number(1~8) ---> ENTER

Eg: input 1 to output 1:

1--> SWITCH ----> 1 ---> ENTER

Inputs Switch to multiple outputs:

number(1~8) ---> SWITCH ---> number(1~8)-->ENTER-->
number(1~8)--->ENTER

Eg: input 2 to output 1,2,3,8:

2 --> SWITCH --> 1 --> ENTER ----> 2 ---> ENTER ----> 3 ---> ENTER
----> 8 ---> ENTER

Scene Save(total 40 scenes):

number(0~9) ---> SAVE

Eg: Save the current switch to scene2:

2--> SAVE(The LCD Screen will show 2 saved)

Scene Recall(total 40 scenes):

number(0~9) ---> RECALL

Eg: Recall the scene10:

10 --> RECALL(The LCD Screen will show 10 loaded)

